## **QF 215<sup>TM</sup>**



## **OVERVIEW**

The QF family features one dual-channel model and one single-channel unit, all incorporating Peavey's legendary low-noise, low-distortion design. Ruggedly constructed, QF Series EQs have 45 mm, center-detented control sliders enclosed in metal for durability. These two rack-space units also offer ±15 dB gain control and an LED display indicating output level. Other shared features include switchable low-cut filters, +21 dBu balanced inputs and outputs, and bypass switches. QF Series equalizer filters are set at ISO center frequencies within 3% accuracy. Whether on stage, in the studio, or simply tweaking your home hi-fi system, the QF Series has an EQ for you.

## **FEATURES**

- Dual channel (15 bands per channel)
- ISO center frequencies within 3% accuracy
- 25 Hz to 16 kHz effective equalization range
- 45 mm, center-detent control sliders enclosed in metal for durability
- Constant Q filters
- 2/3 octave filter sets
- 18 db per octave 40Hz low-cut filter with status LED
- +/-15 dB gain control
- Improved Peavey FLS® (Feedback Locating System)
- XLR and 1/4 inch TRS inputs/outputs for balanced or unbalanced operation
- 2 RU
- 12 dB boost/18 dB cut per band
- Weight Unpacked: 9.00 lb(4.082 kg)
- Weight Packed: 11.00 lb(4.99 kg)
- Width Packed: 6.12"(15.5448 cm)
- Height Packed: 22.25"(56.515 cm)
- Depth Packed: 10.25"(26.035 cm)